

TITLE OF THE INVENTION

SYSTEM FOR OPTICALLY TRANSMITTING FREQUENCY-DIVISION-
MULTIPLEXED SIGNAL AND TRANSMITTER THEREFOR

5 BACKGROUND OF THE INVENTION

Field of the Invention

The present invention relates to optical transmission systems, and more particularly to a system that optically transmits a frequency-division-multiplexed signal obtained by
10 frequency-division-multiplexing a plurality of signals.

Description of the Background Art

FIG. 11 is a block diagram exemplarily showing the configuration of a conventional optical transmission system for
15 transmitting a frequency-division-multiplexed signal. As will be known from FIG. 11, this optical transmission system comprises a multiplexer 1100, an FM modulator 1101, an optical transmitter 1104, an optical receiver 1106, and an FM demodulator 1107. In the optical transmission system, an electrical transmission line
20 1102 connects the FM modulator 1101 and the optical transmitter 1104 to each other, and an optical transmission line 1105 connects the optical transmitter 1104 and the optical receiver 1106 to each other.

The operation of the conventional optical transmission
25 system in the above configuration will be described below. The

multiplexer 1100 frequency-division-multiplexes a plurality of signals, and outputs the resultant signal to the FM modulator 1101. The FM modulator 1101 converts the frequency-division-multiplexed signal into a frequency-modulated signal (hereinafter, referred to as "FM modulated signal") having a predetermined frequency deviation through frequency modulation. After that, the FM modulator 1101 outputs the FM modulated signal to the electrical transmission line 1102. The optical transmitter 1104 receives the FM modulated signal through the electrical transmission line 1102, then converts the signal into an optical signal, and sends the optical signal to the optical transmission line 1105. The optical receiver 1106 receives the optical signal through the optical transmission line 1105, then converts the signal into an FM modulated signal which is an electrical signal, and outputs the FM modulated signal to the FM demodulator 1107. The FM demodulator 1107 demodulates the FM modulated signal to reproduce the original frequency-division-multiplexed signal.

The optical transmission system in the above configuration is described in detail in "Optical Super Wide-Band FM Modulation Scheme and Its Application to Multi-Channel AM Video Transmission Systems" by K. Kikushima et al. (IOOC'95 Technical Digest, Vol. PD2-7, pp.33-34), and other documents. The optical transmission system converts a frequency-division-multiplexed signal into an FM modulated signal, and then optically transmits

and demodulates the FM modulated signal to reproduce the original frequency-division-multiplexed signal. The optical transmission system utilizes an FM gain in the FM transmission to improve the signal-to-noise power ratio (SNR) of the demodulated signal (i.e., the frequency-division-multiplexed signal), thereby enabling high-quality signal transmission.

Thus, the above-described optical transmission system can realize high-quality multi-channel signal transmission with an optical fiber.

However, the above-described system for optically transmitting an FM modulated signal has the following specific problems due to the properties of the FM modulated signal and the nonlinearity of an optical fiber.

An FM modulation scheme increases a frequency deviation to acquire a greater FM gain, thereby enabling signal transmission of higher quality than other modulation schemes such as amplitude modulation. On the other hand, the increased frequency deviation requires a wider signal band. In addition, in the FM modulation scheme, linear distortion tends to occur under the influence of the group delay characteristic of a transmission line and the like (the characteristic that a propagation delay varies depending on a frequency). Therefore, the transmission line must be designed with particular attention. However, as a signal band becomes wider, the group delay variations in the band becomes more difficult to be sufficiently suppressed.

In a general optical modulation scheme, the optical frequency spectrum of an optical signal is composed of a steep-shaped optical carrier component, which has narrow spectral line-width, and upper and lower sidebands, as shown in FIG. 12B.

5 The upper and lower sidebands are geometrically similar to the frequency spectrum of a modulating signal. Therefore, if a wide-band signal like an FM modulated signal is used as a modulating signal in optical modulation, the optical frequency spectrum of the optical signal also becomes wider. The optical
10 signal having such wide optical frequency spectrum becomes susceptible to the chromatic-dispersion of an optical fiber (the characteristic that a propagation delay varies depending on a wavelength). The affected optical signal component interacts with the optical carrier component to induce harmonic distortion
15 in the FM modulated signal, resulting in waveform deterioration of the transmitted signal.

As is known from the above, the conventional optical transmission system has the specific problem that the quality of the transmitted signal is degraded due to the wide-band property
20 of an FM modulated signal.

SUMMARY OF THE INVENTION

Therefore, an object of the present invention is to provide an optical transmission system capable of narrowing the bandwidth
25 of an FM modulated signal while increasing the frequency deviation

the optical transmitter for converting the FM modulated signal
outputted from the FM modulator into a frequency-divided FM
modulated signal whose frequency is $1/2^n$ the frequency of the FM
modulated signal, the n being an integer of not less than 1,

5 wherein the optical modulator modulates the first
unmodulated light with the frequency-divided FM modulated signal
to produce the optical-intensity-modulated signal.

Sub A2
Incl. 5

As stated above, in the sixth aspect, as in the third aspect,
the optical transmission system previously produces in the FM
10 modulator an FM modulated signal having a frequency deviation
larger enough to acquire a desired FM gain, then converts the FM
modulated signal into a frequency-divided FM modulated signal,
and converts the signal into an optical-intensity-modulated
signal for transmission. It is therefore possible to reduce the
15 phase noise in the FM modulated signal to be optically transmitted
and FM demodulated.

According to a seventh aspect, in the first aspect, the
transmission system further comprises,

20 a frequency-divider provided between the FM modulator and
the optical transmitter for converting the FM modulated signal
outputted from the FM modulator into a frequency-divided FM
modulated signal whose frequency is $1/2^n$ the frequency of the FM
modulated signal, the n being an integer of not less than 1,

Sub A3
20

wherein the optical transmitter includes an optical
25 modulator for producing the optical-intensity-modulated signal

Sub 3
encl. 7

through the optical modulation using the frequency-divided FM modulated signal as an original signal.

As described above, in the seventh aspect, the optical transmission system previously produces in the FM modulator an FM modulated signal having a frequency deviation larger enough to acquire a desired FM gain, then converts the FM modulated signal into a frequency-divided FM modulated signal, and next converts the signal into an optical-intensity-modulated signal for transmission. It is therefore possible to reduce the phase noise in the FM modulated signal to be optically transmitted and FM demodulated.

SECRET

An eighth aspect of the present invention is directed to an transmitter for use in a transmission system for optically transmitting a frequency-division-multiplexed signal, which is obtained by frequency-division-multiplexing a plurality of signals, from a transmitting end to a receiving end, comprising:

Sub 4

a multiplexer for frequency-division multiplexing the plurality of signals to produce the frequency-division-multiplexed signal;

an FM modulator for converting the frequency-division-multiplexed signal into a frequency-modulated signal through frequency modulation using the frequency-division-multiplexed signal as an original signal to output the frequency-modulated signal as an FM modulated signal; and

an optical transmitter for converting the FM modulated

Sub A
concl.

through optical modulation using the frequency-divided FM modulated signal as an original signal.

These and other objects, features, aspects and advantages of the present invention will become more apparent from the following detailed description of the present invention when
5 taken in conjunction with the accompanying drawings.

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is a block diagram showing the configuration of an optical transmission system according to a first embodiment of
10 the present invention;

FIG. 2A is a schematic diagram showing the frequency spectrum of an FM modulated signal outputted from an FM modulator in the optical transmission system according to the first
15 embodiment;

FIG. 2B is a schematic diagram showing the optical frequency spectrum of an optical signal outputted from an optical modulator in the optical transmission system according to the first
embodiment;

FIG. 2C is a schematic diagram showing the frequency spectrum of an FM modulated signal outputted from an optical receiver in the optical transmission system according to the first
20 embodiment;

FIG. 3 is a schematic diagram used to explain optical modulation performed by the optical modulator in the optical
25

transmission system according to the first embodiment;

FIG. 4 is a block diagram showing the configuration of an optical transmission system according to a second embodiment of the present invention;

5 FIG. 5A is a schematic diagram showing the frequency spectrum of an FM modulated signal outputted from an FM modulator in a first operation mode of the optical transmission system according to the second embodiment;

10 FIG. 5B is a schematic diagram showing the frequency spectrum of an FM modulated signal outputted from a frequency-divider in the first operation mode of the optical transmission system according to the second embodiment;

15 FIG. 5C is a schematic diagram showing the frequency spectrum of an FM modulated signal outputted from an optical receiver in the first operation mode of the optical transmission system according to the second embodiment;

20 FIG. 6A is a schematic diagram showing the frequency spectrum of an FM modulated signal outputted from the FM modulator in a second operation mode of the optical transmission system according to the second embodiment;

FIG. 6B is a schematic diagram showing the frequency spectrum of an FM modulated signal outputted from the frequency-divider in the second operation mode of the optical transmission system according to the second embodiment;

25 FIG. 6C is a schematic diagram showing the frequency

spectrum of the FM modulated signal outputted from the optical receiver in the second operation mode of the optical transmission system according to the second embodiment;

FIG. 7 is a block diagram showing the configuration of an optical transmission system according to a third embodiment;

FIG. 8 is a block diagram showing the configuration of an optical transmission system according to a fourth embodiment;

FIG. 9 is a schematic diagram used to explain optical modulation performed by an optical modulator in the optical transmission system according to the fourth embodiment;

FIG. 10A is a schematic diagram showing the optical frequency spectrum of an optical signal outputted from the optical modulator in the optical transmission system according to the fourth embodiment;

FIG. 10B is a schematic diagram showing the optical frequency spectrum of a light outputted from an optical branching circuit in the optical transmission system according to the fourth embodiment;

FIG. 10C is a schematic diagram showing the optical frequency spectrum of an optical signal outputted from an optical combining circuit in the optical transmission system according to the fourth embodiment;

FIG. 11 is a block diagram showing the configuration of a conventional optical transmission system;

FIG. 12A is a schematic diagram showing the frequency

spectrum of an FM modulated signal outputted from an FM modulator in the optical transmission system in FIG. 11;

FIG. 12B is a schematic diagram showing the optical frequency spectrum of an optical signal outputted from an optical transmitter in the optical transmission system in FIG. 11; and

FIG. 12C is a schematic diagram showing the frequency spectrum of an FM modulated signal outputted from an optical receiver in the optical transmission system in FIG. 11.

DESCRIPTION OF THE PREFERRED EMBODIMENTS

(First Embodiment)

FIG. 1 shows the configuration of a system for optically transmitting a frequency-division-multiplexed signal according to a first embodiment of the present invention. Referring to FIG. 1, the optical transmission system of the present embodiment comprises a multiplexer 100, an FM modulator 101, a light source 103, an optical modulator 104, an optical receiver 106, and an FM demodulator 107. In the optical transmission system, an electrical transmission line 102 connects the FM modulator 101 and the optical modulator 104 to each other, and an optical transmission line 105 connects the optical modulator 104 and the optical receiver 106 to each other. The optical transmission system transmits an optical signal, which is produced in a below described manner, from a transmitting end to a receiving end through the optical transmission line 105. At the transmitting

end, the light source 103 and the optical modulator 104 constitute an optical transmitter 20a, and the optical transmitter 20a, the multiplexer 100, and the FM modulator 101 constitute a transmitter 10a. In addition, the optical receiver 106 at the receiving end is constituted by a photodetector such as photodiode for converting an optical signal into an electrical signal through photodetection based on a square-law detection characteristic, and a preamplifier for amplifying the electrical signal fed from the photodetector.

Next, referring to FIGS. 2A to 2C, the operation of the present embodiment shown in FIG. 1 is described. FIGS. 2A to 2C are schematically illustrate the frequency spectrums of respective signals in the optical transmission system in FIG. 1. FIG. 2A shows the frequency spectrum of an output signal of the FM modulator 101. FIG. 2B shows the optical frequency spectrum of an output signal (optical signal) of the optical modulator 104. FIG. 2C shows the frequency spectrum of an output signal of the optical receiver 106. In the optical transmission system shown in FIG. 1, the multiplexer 100 frequency-division multiplexes a plurality of signals, and outputs the resultant signal to the FM modulator 101. The FM modulator 101 converts the frequency-division-multiplexed signal into an FM modulated signal through frequency modulation. The FM modulated signal has a frequency spectrum as shown in FIG. 2A in which a carrier frequency is f_c and a frequency deviation is ΔF . After that, the FM modulator

Sub AS
encl. 7

frequency-division-multiplexed signal.

An FM modulation scheme can raise an FM gain by increasing a frequency deviation, and improve the signal-to-noise ratio (SNR) of a demodulated signal. On the other hand, the increase in frequency deviation extends the spectrum bandwidth of an FM modulated signal, and also requires a wider band of a transmission line. The group delay characteristic of the transmission line with such wide band affects the FM modulated signal, to cause linear distortion thereof in some cases. That is, as the bandwidth of an FM modulated signal is wider, waveform distortion thereof increases. In short, a frequency deviation in FM modulated signal transmission has a trade-off relation between noise characteristic and waveform distortion of an FM modulated signal. Hence, the wide-band FM transmission system is difficult to optimally design.

The optical transmission system in FIG. 1 converts an FM modulated signal into an optical signal whose optical carrier is suppressed, and then optically transmits and square-law detects the optical signal, thus producing an FM modulated signal having a frequency deviation (or frequency bandwidth) twice as large as the one of the original FM modulated signal. Therefore, the frequency deviation of the FM modulated signal outputted from the FM modulator 101 is set to be half of the frequency deviation essentially required to acquire a predetermined FM gain in FM demodulation. The optical transmission system thus reduces the

bandwidth of the FM modulated signal in half at the transmitting end, and reduces linear distortion caused by the group delay characteristic of the electrical transmission line 102 and the like while securing the predetermined FM gain. Moreover, the optical transmission system suppresses the optical carrier level of the optical signal, thereby suppressing waveform deterioration due to the chromatic-dispersion of the optical fiber transmission line. As is clear from the above, the optical transmission system of the present embodiment can realize high-quality signal transmission, and facilitate implementation of a transmission line to reduce the cost of the entire system.

(Second Embodiment)

FIG. 4 shows the configuration of an optical transmission system of an FM modulated signal according to a second embodiment of the present invention. Referring to FIG. 4, the optical transmission system of the present embodiment comprises the multiplexer 100, the FM modulator 101, the light source 103, the optical modulator 104, the optical receiver 106, the FM demodulator 107, and a frequency-divider 408. In the optical transmission system, the electrical transmission line 102 connects the frequency-divider 408 and the optical modulator 104 to each other, and the optical transmission line 105 connects the optical modulator 104 and the optical receiver 106 to each other. The configuration of the second embodiment is different from that

of the above-described first embodiment only in including the frequency-divider 408. Therefore, the constituents identical to those in the first embodiment are assigned the same reference numerals, and the description thereof is simplified herein. The difference from the first embodiment is mainly described below. Note that at the transmitting end of the optical transmission system of the present embodiment, the light source 103 and the optical modulator 104 constitute the optical transmitter 20a, and the optical transmitter 20a, the multiplexer 100, the FM modulator 101, and the frequency-divider 408 constitute the transmitter 10b.

In the above first embodiment, an FM modulated signal is outputted from the FM modulator 101, and then directly applied to the optical modulator 104. On the other hand, in the present embodiment, the frequency-divider 408 divides each frequency component of the FM modulated signal outputted from the FM modulator 101 into 2^n (n is an integer of not less than one). Namely, the frequency-divider 408 converts the FM modulated signal into a frequency-divided FM modulated signal whose frequency is $1/2^n$ the frequency of the FM modulated signal. The frequency-divider 408 then outputs the frequency-divided FM modulated signal to the optical modulator 104.

In an FM modulation scheme, if an oscillator for generating an FM modulated signal has frequency drift, which is called "phase noise", the frequency drift is converted into intensity noise at

the FM demodulation to degrade the noise characteristic of the demodulated signal.

The optical transmission system shown in FIG. 4 produces an FM modulated signal having a frequency deviation more than the
5 frequency deviation essentially required to acquire a predetermined FM gain in FM demodulation. Next, the optical transmission system converts the FM modulated signal into a frequency-divided FM modulated signal, and then converts the signal into an optical signal for transmission. The phase noise
10 in the FM modulated signal received at the receiving end is thus reduced.

FIGS. 5A to 5C illustrate the operation and advantageous effects of the frequency-divider 408 in a first operation mode of the optical transmission system. FIGS. 5A, 5B, and 5C
15 schematically show the frequency spectrums included in output signals of the FM modulator 101, the frequency-divider 408, and the optical receiver 106, respectively. In the first operation mode, as shown in FIGS. 5A to 5C, the optical transmission system previously produces an FM modulated signal (whose phase noise is
20 $\Delta \nu$) having a frequency deviation ΔF equal to a required amount of frequency deviation ΔF in FM demodulation (FIG. 5A). After that, the FM modulated signal is converted into a frequency-divided FM modulated signal whose frequency is 1/2 the frequency of the FM modulated signal (FIG. 5B). Then, the frequency-divided
25 FM modulated signal is converted into an optical signal whose

optical carrier is suppressed, and square-law detected. As a result, the optical transmission system obtains an FM modulated signal having phase noise $\Delta \nu$ equal to the one of the original FM modulated signal (FIG. 5C). On the other hand, in the first embodiment, the phase noise of the FM modulated signal becomes twice at the receiving end while the frequency deviation thereof is large (FIG. 2C). Specifically, when the phase noise of the FM modulated signal at the transmitting end is $\Delta \nu$, it becomes $2 * \Delta \nu$ at the receiving end.

FIGS. 6A to 6C illustrate the operation and advantageous effects of the frequency-divider 408 in a second operation mode of the optical transmission system in FIG. 4. FIGS. 6A, 6B, and 6C schematically show the frequency spectrums included in output signals of the FM modulator 101, the frequency-divider 408, and the optical receiver 106, respectively. In the second operation mode, as shown in FIGS. 6A to 6C, the optical transmission system previously produces an FM modulated signal (whose phase noise is $\Delta \nu$) having a frequency deviation $2 * \Delta F$ twice as large as a required amount of frequency deviation ΔF in FM demodulation (FIG. 6A). After that, the FM modulated signal is converted into a frequency-divided FM modulated signal whose frequency is 1/4 the frequency of the FM modulated signal (FIG. 6B). The frequency-divided FM modulated signal is next converted into an optical signal, then transmitted, and square-law detected. Thus, the optical transmission system can obtain an FM modulated signal

whose phase noise is reduced in half of the one of the original FM modulated signal (i.e., the phase noise after transmission becomes $1/2 * \Delta \nu$) (FIG. 6C).

As is clear from the above, the optical transmission system
5 of the present embodiment can reduce the phase noise in the FM modulated signal after transmission, thereby realizing signal transmission of better quality.

(Third Embodiment)

10 FIG. 7 shows the configuration of an optical transmission system of an FM modulated signal according to a third embodiment of the present invention. Referring to FIG. 7, the optical transmission system of the present embodiment comprises the multiplexer 100, the FM modulator 101, the light source 103, the
15 optical modulator 104, the optical receiver 106, the FM demodulator 107, and an amplitude controller 709. In the optical transmission system, the electrical transmission line 102 connects the amplitude controller 709 and the optical modulator 104 to each other, and the optical transmission line 105 connects
20 the optical modulator 104 and the optical receiver 106 to each other. The configuration of the third embodiment is different from that of the first embodiment in including the amplitude controller 709. Therefore, the constituents identical to those of the first embodiment are assigned the same reference numerals,
25 and the description thereof is simplified herein. The difference

from the first embodiment is mainly described below. Note that at the transmitting end of the optical transmission system of the present embodiment, the light source 103 and the optical modulator 104 constitute the optical transmitter 20a, and the optical transmitter 20a, the multiplexer 100, the FM modulator 101, and the amplitude controller 709 constitute the optical transmitter 10c.

In the above first embodiment, an FM modulated signal is outputted from the FM modulator 101, and directly applied to the optical modulator 104. On the other hand, in the present embodiment, the amplitude controller 709 removes variations in amplitude of the FM modulated signal to adjust the amplitude to consistently remain constant, and then outputs the FM modulated signal to the optical modulator 104.

As described in the above, in the optical transmission system in FIG. 7, the amplitude of an FM modulated signal to be applied to the optical modulator 104 consistently remains constant. Accordingly, the optical transmission system can avoid the influence of the nonlinearity in electrical-to-optical conversion performed by the optical modulator 104, and prevent the signal quality from being degraded in FM demodulation performed by the FM demodulator 107. Consequently, it is possible to realize high-quality signal transmission.

(Fourth Embodiment)

FIG. 8 shows the configuration of an optical transmission system of an FM modulated signal according to a fourth embodiment of the present invention. Referring to FIG. 8, the optical transmission system of the present embodiment comprises the multiplexer 100, the FM modulator 101, the light source 103, the optical receiver 106, the FM demodulator 107, an optical modulator 804, an optical branching circuit 810, an optical combining circuit 811, and an optical delay circuit 812. In the optical transmission system, the electrical transmission line 102 connects the FM modulator 101 and optical modulator 104 to each other, and the optical transmission line 105 connects the optical combining circuit 811 and the optical receiver 106 to each other. The fourth embodiment is different from the first embodiment in including the optical branching circuit 810, the optical combining circuit 811, and the optical delay circuit 812. In addition, the conditions for optical modulation performed by the optical modulator 804 are different from those of the optical modulator 104 in the first embodiment. Therefore, the constituents identical to those in the first embodiment are assigned the same reference numerals, and the description thereof is simplified herein. The difference from the first embodiment is mainly described below. Note that at the transmitting end of the optical transmission system of the present embodiment, the light source 103, the optical branching circuit 810, the optical modulator 804, the optical combining circuit 811, and the optical

delay circuit 812 constitute the optical transmitter 20b, and the optical transmitter 20b, the multiplexer 100, and the FM modulator 101 constitute the transmitter 10d.

In the above-described first embodiment, the optical modulator 104 is biased at the "valley" in its input-voltage vs. output-optical-power characteristic to produce an optical signal whose optical carrier is suppressed. However, in the present embodiment, the optical modulator 804 is biased in its input-voltage vs. output-optical-power characteristic at the "peak" where the output optical power is at the maximum, as shown in FIG. 9. An FM modulated signal is applied to the optical modulator 804 with respect to the voltage of an operating point 1002 which is set by the above-mentioned bias. The optical modulator 804 thus produces an optical-intensity-modulated signal (hereinafter, referred to as "optical signal") having an optical frequency spectrum as shown in FIG. 10A. The optical branching circuit 810 receives an unmodulated light (shown in FIG. 10B) from the light source 103, and branches the light into a first unmodulated light La and a second unmodulated light Lb. The first unmodulated light La is outputted to the optical modulator 804, and converted into an optical signal through optical modulation using the FM modulated signal outputted from the FM modulator 101 as an original signal. The second unmodulated light Lb is outputted through the optical delay circuit 812 to the optical combining circuit 811, and combined therein with the optical

signal outputted from the optical modulator 804. The optical delay circuit 812, after receiving the second unmodulated light Lb, controls a propagation delay thereof to set the second unmodulated light Lb in a precisely opposite phase to the optical signal outputted from the optical modulator 804. Thus, in the optical combining circuit 811, the optical carrier component of the optical signal outputted from the optical modulator 804 is canceled by the unmodulated light outputted from the optical delay circuit 812. Consequently, the optical transmission system produces an optical signal having the optical frequency spectrum in which an optical carrier component is suppressed as shown in FIG. 10C.

As is clear from the above, according to the optical transmission system in FIG. 8, the optical carrier component of the optical signal outputted from the optical modulator 804 is cancelled by the unmodulated light Lb which is one of the lights branched from the unmodulated light fed from the light source 103. The optical transmission system thus produces an optical signal whose optical carrier component is suppressed, thereby realizing high-quality signal transmission.

The optical delay circuit 812 is interposed onto the path leading from the optical branching circuit 810 directly to the optical combining circuit 811 in the fourth embodiment, but may be interposed onto the path leading from the optical branching circuit 810 to the optical combining circuit 811 via the optical

modulator 804 or interposed onto the both paths, or may be omitted.

In addition, it is possible to apply the change of the conditions for the optical modulation performed by the optical modulator 804, and the change and addition of the configuration accompanied therewith (the optical branching circuit 810, the optical combining circuit 811, and the optical delay circuit 812), all of which are described in the fourth embodiment, to the first embodiment and other embodiments. In such case, the same advantageous effects can be also provided.

While the invention has been described in detail, the foregoing description is in all aspects illustrative and not restrictive. It is understood that numerous other modifications and variations can be devised without departing from the scope of the invention.